



## Troffer Retrofit Kit

### Reflector Kit - Retrofit 2 or 3 Lamp for Troffer Body

These kits provide everything required to enhance the performance and energy savings of your recessed fixture while minimizing labor, clean up and expense. Choice of highly polished mirrored reflector or enhanced white reflector, both designed to maximize output and efficiency.

#### MATERIALS

Reflectors are a premium and standard full specular mirrored aluminum, and enhanced white. Socket Bars are white. Code guage steel.

#### Ordering Information

Example: HSL-22C2M20BL10

| Series               | # of Lamps       | Reflector                           | Socket Bar & Type  | Ballast Manufacture                          | Ballast Model              | Ballast Factor          | Voltage                   | Configuration                                      |
|----------------------|------------------|-------------------------------------|--|--|----------------------------|-------------------------|---------------------------|--|
| <b>HSL-14C</b> 1 X 4 | <b>1</b> 1 Lamp  | <b>M20</b> Mirrored Reflector       | <b>BL10</b> Socket Bar & Instant Start (Standard for T8) | <b>Blank</b> No Preference                   | <b>Blank</b> Stand Version | <b>Blank</b> Normal .88 | <b>Blank</b> Less Ballast | <b>Blank</b> Components bulkpacked and unassembled |
| <b>HSL-22C</b> 2 X 2 | <b>2</b> 2 Lamps |                                     |  | <b>F</b> Universal                           | <b>W</b> Premiere Version  | <b>H</b> High 1.18      | <b>MV</b> 120v-277v       |  |
| <b>HSL-24C</b> 2 X 4 | <b>3</b> 3 Lamps | <b>W10</b> Enhanced White Reflector | <b>BL11</b> Socket Bar & Program Start (Standard for T5) | <b>Y</b> Sylvania                            | <b>P</b> Program Start     | <b>L</b> Low .77        | <b>E480</b> 480V          | <b>WR</b> Wire Ballasts and Sockets Together       |
|                      | <b>4</b> 4 Lamps |                                     |  | <b>Z</b> GE                                  |                            | <b>NN</b> 1.00          |                           |  |
|                      |                  |                                     |  | <b>ZH MV</b> GE Multi Volt H Ballast (73190) |                            | <b>LL</b> Ultra Low.66  |                           |  |

1. Add T5 if using T5 Lamps (Up to two lamps only in 14

#### Popular Kits

| Item Number     | Dimension ( LxWxH)         | Lamping |
|-----------------|----------------------------|---------|
| HSL-22CM20BL10  | 2 X 2 Troffer Retrofit Kit | 2-F17T8 |
| HSL-22CW10BL10  | 2 X 2 Troffer Retrofit Kit | 2-F17T8 |
| HSL-24CM20BL10  | 2 X 4 Troffer Retrofit Kit | 2-F32T8 |
| HSL-22C2W10BL10 | 2 X 4 Troffer Retrofit Kit | 2-F32T8 |

L10 is for Short, shunted, snap fit lamp holders (For IS ballasts). Change to L11 for short, unshunted, snap fit (for RS and ProStart ballasts). M20 is mirrored reflector and W10 is enhanced white aluminum reflector.

